

Changed log:

1. Recovery mode(update screen) only display English characters, delete Chinese characters.
2. Add a function to detect hardware version automatically, it will install corresponding firmware when you update next time.

Update:

Download 20110907 SPI file from here:

<http://www.geniatech.com/down-eng/Androidtvbox/20110907SPI.zip>

After downloading, you will see four files within it:

update_spi_256.zip for ATV300 and ATV1000 256MB

update_spi_512.zip for ATV1000 512MB

update_spi_512F.zip for ATV1000 V2.2 512(you can find V2.2 512 information on the back of the box, if not, use above 256 or 512 SPI)

version.txt New Uboot version and recovery version.

If you are using ATV300 or ATV1000 with 256MB, change update_spi_256.zip name to update.zip, don't unzip and copy it to SD card (only), then update it with either of two solutions as below:

1. Connect SD card to the box, and go to setting->privacy->update system->update box to update SPI, it will reboot after finished.
2. Connect SD card to the box, press the black button on the back of the ATV1000/the black button beside the ATV300, and re-plug power adapter, then you will see update screen, release the button at this time, it will reboot after finished. (if the screen shows update failed, this is because the box doesn't find update.zip file, please re-plug SD card or try another one)

If you are using ATV1000 512MB, change update_spi_512.zip name to update.zip, don't unzip, and copy it to SD card (only), then update it with either of two solutions as above.

If you are using ATV1000 V2.2 512, change update_spi_512F.zip name to update.zip, don't unzip, and copy it to SD card (only), then update it with either of two solutions as above.

After updating, go to setting->about device, check Uboot version is V1.3.5(20110906), recovery version is 1.2.9 (20110907), ignore Kernel version and build number.